Autonics

This is only for reference, the actual product does not support all combinations. For selecting the specified model, follow the Autonics website.

| GP - A 0 - T 2 D 3 |
|---|
|---|

O Screen size 046: 4.6 inch 057: 5.7 inch 070: 7.0 inch

Ordering Information

104: 10.4 inch

Display color 8: 262,144 color

9: 16,777,216 color

Interface

| Model | € | RS232C | RS422 | CAN | Micro SD | USB Host | USB Device | Ethernet |
|-------------|---|--------|-------|-----|----------|-------------|---------------|----------|
| GP-A | 6 | 1 | 1 | - | - | 1 | 1 1 | |
| 046/057/070 | 7 | 2 | - | - | - | | | 1 |
| GP-A104 | 8 | 1 | 1 | 1 | 1 | | | |
| GP-A104 | 9 | 2 | - | 1 | 1 | | | |

Product Components

Graphic panel + built in battery

• 4.6 / 5.7 / 7.0 inch: 4 fixing brackets

• 10.4 inch: 6 fixing brackets, CAN connector

Sold separately: communication cable

Specifications

Protection structure

environment)

IP65 (front panel, IEC standard)

| | GP-A046 | GP-A057 | GP-A070 | GP-A104 | | | |
|-----------------------------------|--|------------------------|---------------------------|---------------------------|--|--|--|
| Screen size | 4.6 inch | 5.7 inch | 7.0 inch | 10.4 inch | | | |
| LCD type | TFT Color LCD | | | | | | |
| Resolution | 800×320 pixel | 640×480 pixel | 800×480 pixel | 800×600 pixel | | | |
| Display area | 108×43.2 mm | 115.2×86.4 mm | 154.4×93.44 mm | 211.2×158.4 mr | | | |
| Display color | 16,777,216 color | 262.144 color | 16,777,216 color | 16,777,216 color | | | |
| LCD view angle | Within 75°/70° | Within 70°/70° | Within 50°/60° | Within 60°/70° | | | |
| top/bottom/left/right) | /80°/80° of each | /80°/80° of each | /65°/65° of each | /80°/70° of each | | | |
| Backlight | White LED | | | | | | |
| Luminance adjustment | Adjustable by sof | tware | | | | | |
| Fouch | Resistive type (4-) | wire) | | | | | |
| Approval | CE 🕼 | | | | | | |
| Unit weight | ≈ 272 g | ≈ 489 g | ≈ 520 g | $\approx 1.07 \text{kg}$ | | | |
| (packaged) | (≈ 382 g) | (≈ 644 g) | (≈ 706 g) | (≈ 1.62 kg) | | | |
| | | | | | | | |
| Serial interface | RS232C, RS422 | | | | | | |
| JSB interface | USB Host, USB De | · / | | | | | |
| Ethernet interface | IEEE802.3(U), 10/100Base-T | | | | | | |
| CAN interface | 24V CAN transceiver | | | | | | |
| External storage | Micro SD up to 32GB (FAT16/32) | | | | | | |
| Real-time controller | RTC embedded | | | | | | |
| Battery life cycle | 3 years at 25°C | | | | | | |
| Supportive interface can be diffe | erent up to model. Fo | r the detailed informa | ation, please refer to 'O | Ordering Informatio | | | |
| Language | Korean, English | | | | | | |
| Text | Bitmap and vector font | | | | | | |
| Memory for user screen | 64MB | | | | | | |
| Number of user screen | 100 pages | | | | | | |
| | | | | | | | |
| Power supply | 24 VDC | | | | | | |
| Allowable voltage range | 90 to 110% of power supply | | | | | | |
| Power consumption | $4.6 \text{ inch}: \le 4.8 \text{ W}, 5.7 / 7.0 \text{ inch}: \le 7.2 \text{ W}, 10.4 \text{ inch}: \le 8.0 \text{ W}$ | | | | | | |
| Insulated resistance | \geq 100 M Ω (500 VDC megger) (between all terminals and case) | | | | | | |
| Ground | $3 \text{rd} \text{grounding} (\leq 100 \Omega)$ | | | | | | |
| Noise immunity | The square wave n | oise (pulse width: 1µ | s) by the noise simula | ator \pm 0.5 kV | | | |
| Dielectric strength | - | 4 1 | , , | | | | |
| Vibration | 500 VAC~ 50/60 Hz for 1 minute (between all terminals and case) 0.75 double amplitude at frequency of 10 to 55 Hz in each X, Y, Z direction for 1 hour | | | | | | |
| Vibration (malfunction) | | ude at frequency o | f 10 to 55 Hz in each | X, Y, Z | | | |
| Shock | | | direction for 2 time- | | | | |
| Shock | | | direction for 3 times | | | | |
| Shock (malfunction) | 100 m/s ² (approx. 10 G) in each X, Y, Z direction for 3 times 0 to 50°C, storage: -20 to 60°C (a non freezing or condensation environment) | | | | | | |
| Ambient temperature | | | | | | | |
| Ambient humidity | 35 to 85%RH, stor | age: 35 to 85%RH (| (a non freezing or co | ndensation | | | |
| | | | | | | | |

• Equipped with TFT LCD for realizing True color

- Horizontal/Vertical installation according to environment
- Available to monitor device of the connected controllers even without user screen data
- Using user screen drawing program 'atDesigner'
- : More variety functions, objects and library image
- : Intuitive user interface
- : Multilingual table function: switching language of user screen by touching a button
- Various communication interface: RS232C, RS422, Ethernet, CAN

CATALOG

Features

GP-A Series

For your safety, read and follow the considerations written in the instruction manual, other manuals and Autonics website.

Color LCD Graphic Panel

口) ×


Device Monitoring

ŝ

The specifications, dimensions, etc. are subject to change without notice for product improvement. Some models may be discontinued without notice.

Dimensions

• Unit: mm, For the detailed dimensions of the product, follow the Autonics web site.




| | ~ | | - C | | - | • |
|-----------|-----|-------|-------|-----|------|-----|
| 4.6 inch | 135 | 143.5 | 75.5 | 6.5 | 36 | 67 |
| 5.7 inch | 160 | 168.5 | 128.5 | 6.5 | 36 | 120 |
| 7.0 inch | 185 | 194 | 134 | 6.5 | 28.5 | 125 |
| 10.4 inch | 260 | 273 | 212 | 7.2 | 34 | 200 |

• Panel cut-out

| | A | В | С |
|-----------|-----------------------|-----------------------|-------------|
| 4.6 inch | 135.5+1.1 | 67.5 ^{+1.1} | \leq 4-R3 |
| 5.7 inch | 160.5 ^{+1.0} | 120.5 ^{+1.0} | \leq 4-R3 |
| 7.0 inch | 186'0 | 126+1.0 | \leq 4-R3 |
| 10.4 inch | 260.5 ^{+1.1} | 200.5 0 | \leq 4-R3 |

• Fixing bracket



Software

Visit Autonics web site to download software.

atDesigner

atDesigner is for editing project file.

Recommended computer specification for atDesigner is as below.

| Item | Recommended spec |
|------------------|-----------------------------|
| Operating system | Windows 7/10 |
| CPU | Intel Core i5-2nd gen. 2500 |
| Memory | 8GB |
| Hard disk | 8GB free space |
| Resolution | 1920×1080 |

• Firmware

Please refer to 'GP-A Series user manual' for firmware upgrade.